

**Amendments to Claims:**

This listing of claims will replace all prior versions and listings of the claims in the application:

**Listing of Claims:**

1. (Previously Presented) A digital device capable of recharging a rechargeable battery comprising:

a consuming current detect unit for detecting a consuming current input to the digital device;

a control unit for generating a control signal based on the consuming current and a battery recharging current;

a recharging current detect unit for detecting the battery recharging current as the battery is recharged; and

a recharging control unit for regulating the current to the rechargeable battery in proportion to the control signal output from the control unit and the battery recharging current detected by the recharging current detect unit.

2. (Original) The digital device capable of recharging a rechargeable battery according to claim 1, wherein the control signal includes a pulse width modulation signal.

3. (Previously Presented) The digital device capable of recharging a rechargeable battery according to claim 2, wherein the pulse width modulation control signal has a duty ratio adjusted according to the consuming current detected by the consuming current detect unit.

4. (Original) The digital device capable of recharging a rechargeable battery according to claim 1, wherein the consuming current detect unit comprises:

a first current detecting resistor for detecting the consuming current; and

a first operational amplifier, wherein a first end of the first current detecting resistor is coupled to an inverting input of the first operational amplifier and the second end of the first current detecting resistor is coupled to the non-inverting input of the first operational amplifier.

5. (Previously Presented) The digital device capable of recharging a rechargeable battery according to claim 1, wherein the recharging current detect unit comprises:

a second current detecting resistor;

a third current detecting resistor for detecting the rechargeable battery recharging current; and

a second operational amplifier, wherein a first end of the second current detecting resistor is coupled to a non-inverting input of the second operational amplifier and to the negative terminal of the rechargeable battery, and a first end of the third current detecting resistor is coupled to an inverting input of the second operational amplifier, and further wherein the second end of the second and third current detecting resistors are coupled together to earth ground.

6. (Original) The digital device capable of recharging a rechargeable battery according to claim 1, wherein the recharging control unit comprises:

an integrator, an input of which is coupled to a first output of the control unit;

a third operational amplifier;

a fourth current detecting resistor; and

a transistor, wherein a first output of the integrator is coupled to a non-inverting input of the third operational amplifier, an inverting input of the third operational amplifier is coupled to an output of the recharging current detect unit, a first end of the fourth current detecting resistor is coupled to an output of the third operational amplifier and a second end of the fourth current detecting resistor is coupled to a first input of the transistor, a second input of the transistor is coupled to a power source, and an output of the transistor is coupled to a positive terminal of the rechargeable battery.

7. (Original) The digital device capable of recharging a rechargeable battery according to claim 1, wherein the control unit includes a microprocessor.

8. (Previously Presented) A method for controlling recharging current of a rechargeable battery used in a digital device comprising:

detecting a consuming current input to the digital device;

detecting a battery recharging current as the battery is recharged;

generating a control signal based on said detected consuming current and said

detected battery recharging current; and

regulating the recharging current to the rechargeable battery in proportion to the control signal and the detected battery recharging current.

9. (Previously Presented) The method for controlling recharging current of a rechargeable battery according to claim 8, wherein the control signal is a pulse width modulation signal.

10. (Original) The method for controlling recharging current of a rechargeable battery according to claim 8 further comprising:

adjusting the control signal according to the detected consuming current.

11. (Original) The method for controlling recharging current of a rechargeable battery according to claim 8, further comprising:

displaying a recharging complete message if the recharging current equals a predetermined value.

12. (Previously Presented) The method for controlling recharging current of a rechargeable battery according to claim 10, wherein the step of adjusting the control signal according to the detected consuming current comprises:

determining whether the magnitude of the consuming current increases or decreases;  
and

varying the control signal in accordance with the increase or decrease of the magnitude of the consuming current.

13. (Previously Presented) The method for controlling recharging current of a rechargeable battery according to claim 9, further comprising:

outputting the control signal according to a magnitude of the consuming current.

14. (Previously Presented) The method for controlling recharging current of a rechargeable battery according to claim 13, wherein the step of outputting the control signal according to a magnitude of the consuming current comprises:

maintaining the pulse width modulation duty cycle substantially at a first constant for

a first range of consuming current values;

maintaining the pulse width modulation duty cycle substantially at a second constant for a second range of consuming current values; and

varying the pulse width modulation duty cycle linearly from about the first constant to about the second constant, for a third range of consuming current values.

15. (Previously Presented) The method for controlling recharging current of a rechargeable battery according to claim 14, wherein the first constant is in the range of about 50 to about 60 percent duty cycle.

16. (Previously Presented) The method for controlling recharging current of a rechargeable battery according to claim 14, wherein the second constant is in the range of about 20 to about 30 percent duty cycle.

17. (Previously Presented) The method for controlling recharging current of a rechargeable battery according to claim 14, wherein the first range of consuming current values is in the range of at or about 0 milliamps to at or about 275 milliamps.

18. (Previously Presented) The method for controlling recharging current of a rechargeable battery according to claim 14, wherein the second range of consuming current values is in the range of about 950 milliamps to about 1200 milliamps.

19. (Previously Presented) The method for controlling recharging current of a rechargeable battery according to claim 14, wherein the third range of consuming current values is in the range of about 275 milliamps to about 950 milliamps.

20. (Currently Amended) A method for recharging a rechargeable battery in a digital device comprising:

determining whether a voltage of the rechargeable battery is greater than 5 volts, and if so, determining that the battery is partially discharged and performing a recharge operation according to a state of the digital device being used;

wherein performing a recharge operation according to the state of the digital device being used comprises:

determining a consuming current;  
outputting a pulse width modulation control signal according to a magnitude  
of the consuming current; and  
supplying a recharging current according to the pulse width modulation  
control signal to the rechargeable battery for recharging.

21. (Previously Presented) The method according to claim 20 wherein the step of performing a recharge operation according to a state of the digital device being used comprises:

determining a consuming current;  
outputting a control signal according to the consuming current; and  
supplying a recharging current according to the control signal to the rechargeable battery for recharging.

22. (Original) The method according to claim 21 wherein the control signal includes a pulse width modulation signal.

23. (Previously Presented) The method according to claim 22 wherein the step of supplying a recharging current according to the pulse width modulation control signal to the rechargeable battery comprises:

determining whether the recharging current is between approximately 1000 and 300 milliamps, and if so, illuminating an illumination device at least one time; and  
determining if the recharging current reaches 300 milliamps within 12 hours, and if so, switching to a second recharge mode.

24. (Previously Presented) The method according to claim 23 wherein the step of switching to a second recharge mode comprises:

charging the rechargeable battery for a first time period of substantially one hour at a recharging current of less than or equal to 300 milliamps and illuminating the illumination device for substantially one hour; and  
illuminating the illumination device continuously after the first time period has elapsed.

25. (Previously Presented) The method according to claim 21, further comprising:  
determining that the recharging current does not reach 300 milliamps within 12 hours,  
and checking the battery voltage; and  
determining whether the voltage of the rechargeable battery is greater than 7 volts,  
and if so, illuminating an illumination device continuously.

26. (Previously Presented) The method according to claim 25, further comprising:  
determining that the voltage of the rechargeable battery is less than or equal to 7 volts;  
and  
displaying an error message and terminating the recharge.

27. (Previously Presented) The method according to claim 20, further comprising:  
determining that the voltage of the rechargeable battery is less than or equal to 5 volts;  
supplying a recharge current to the battery for approximately 2 seconds at about 80  
milliamps; and  
determining whether the voltage of the rechargeable battery is more than 5 volts, and  
if so, performing a quick recharge, otherwise performing a trickle recharge.

28. (Previously Presented) The method according to claim 27, wherein performing  
the trickle recharge comprises:  
supplying approximately 80 milliamps to the battery for approximately one-half hour  
and illuminating an illumination device momentarily; and  
determining whether the voltage of the rechargeable battery is greater than  
approximately 5 volts after the approximately one half hour of recharging, and if so,  
performing a recharge operation according to the state of the digital device being used.

29. (Cancelled)

30. (Currently Amended) The method according to claim 20[[29]] wherein the  
step of supplying a recharging current according to the pulse width modulation control signal  
to the rechargeable battery comprises:  
determining whether the recharging current is between approximately 1000 and 300  
milliamps, and if so, illuminating an illumination device at least one time; and

determining if the recharging current reaches 300 milliamps within 12 hours, and if so, switching to a second recharge mode.

31. (Previously Presented) The method according to claim 30 wherein the step of switching to a second recharge mode comprises:

charging the rechargeable battery for a first time period of substantially one hour at a recharging current of less than or equal to 300 milliamps and illuminating the illumination device for substantially one hour; and

illuminating the illumination device continuously after the first time period has elapsed.

32. (Previously Presented) The method according to claim 28, further comprising:  
determining that the recharging current does not reach 300 milliamps within 12 hours, and checking the voltage of the rechargeable battery; and

determining whether the voltage of the rechargeable battery is greater than 7 volts, and if so, illuminating an illumination device continuously.

33. (Previously Presented) The method according to claim 32, further comprising:  
determining that the voltage of the rechargeable battery is less than or equal to 7 volts;  
and

displaying an error message and terminating the recharge.

34. (Previously Presented) The method according to claim 27, further comprising:  
determining that the voltage of the rechargeable battery is less than or equal to approximately 5 volts within approximately one half hour; and

determining whether the recharge current is not more than approximately 30 milliamps for approximately 2 seconds, and if not, continuing to recheck the magnitude and duration of the trickle recharge and if so, displaying an error message and terminating the recharge.

35. (Previously Presented) The method according to claim 12 wherein the control signal is a pulse width modulation signal and the step of varying the control signal comprises varying the duty cycle of the pulse width modulation signal.

36. (Withdrawn) A battery recharging device for charging a digital device, the device comprising:

- an adapter for supplying a power source to a battery of the digital device;
- a recharging current detect unit for detecting a charging current of the battery;
- an LED display unit for displaying the recharging state of the battery according to the detection result of the recharging current detect unit; and
- a control unit for controlling the LED display unit so that the LED display unit switches on and off a predetermined number of times if a current lower than a predetermined reference is detected, and for controlling the LED display unit so that the LED display unit lights if a current higher than a predetermined reference is detected according to the detection result of the recharging current detect unit.

37. (Withdrawn) The device according to claim 36, further comprising a consuming current detect unit for detecting a consuming current inputted from the battery recharging device to the digital device.